

Modify the Added camera

If you need to modify the added camera, please click  to view the added camera list, or

click  -> Device Management->CAM List to view the added camera.

Use the up, down, and top button of the joystick to move the cursor and select the camera to be modified.

Use the left, right, and top button of the joystick to operate Add Group/Edit/Add/Delete below.

CAM List			
CAM1(1,2)	Camera-G50.V	192.168.1.208	Sony VISCA
CAM2(2)	Camera-	192.168.1.88	Sony VISCA
CAM3(1)	Camera-In	192.168.1.208	ONVIF
CAM4(1)	Camera	1-9600	PELCO D
CAM5	Camera-KEYBOARD ...	192.168.1.125:5961	NDI®
CAM6	Camera-KEYBOARD ...	192.168.1.103:5961	NDI®
Add Group	Edit	Add	Delete

For NDI Camera:

Only the parameters of manually added NDI cameras can be modified. For NDI cameras added by automatic search, only the camera name can be modified.

For ONVIF cameras:

After adding the camera, you can enter the camera modification page to modify the default configuration of the ONVIF camera to determine whether the ZowieKBD preview is a sub-stream or a main stream.

CAM3(In-ONVIF-rtsp://192.168.1.208:554/stream1)		
Username	admin >	
Password	admin >	
RTSP Auth	Off >	
RTSP Username	admin >	
RTSP Password	admin >	
Profiles	mainStream_Profile-Token ▾	
Save	Select	Delete