

Add an ONVIF Camera to ZowieKBD

Method 1: Search for ONVIF cameras (Recommended)

Click  and select ONVIF protocol to search or click  -> Device Management->Search and select ONVIF protocol to search.



ONVIF Discovery				
1	IPCamera	192.168.1.6	8000	-
2	ZowiePTZ-00001	192.168.1.23	2000	-
3	ZowieBox-23455	192.168.1.45	2000	-
4	ZowieBox-SDI-00001	192.168.1.47	2000	-
5	ZowiePTZ-66128	192.168.1.64	2000	-
6	ZowiePTZ-2212	192.168.1.76	2000	-
Add		Check All	Search	

After the search is completed, use the up, down and top button of the joystick to select the camera to add. A " ✓ " sign will appear in front of the selected camera .

Use the left, right and top button of the joystick to operate Add/Check All/Search below. When clicking to add a single camera, please select the correct ONVIF authentication and RTSP authentication. (This step is not required when adding ONVIF cameras in batches)



192.168.1.208(In-ONVIF)	
Port	81 >
Auth Mode	NONE ∨
Username	admin >
Password	admin >
RTSP Auth	Off >
RTSP Username	admin >
Add	

Method 2: Manually add ONVIF camera

Click  to add manually or click  -> Device Management->CAM List->Add to add manually.

Use the up, down and top buttons of the joystick to move the cursor and modify the parameters.

Add Camera	
Name	Camera >
Type	ONVIF ∨
Cam	Auto ∨
IP Addr	192.168.1.148 >
Port	2000 >
Auth Mode	NONE ∨
Add	

Select ONVIF as the type and enter the IP address and port number of the ONVIF camera (the default port number for most cameras is 2000).

Cam numbers can be specified or automatically assigned in the order.

Add Camera	
Auth Mode	NONE ∨
Username	admin >
Password	admin >
RTSP Auth	Off >
RTSP Username	admin >
RTSP Password	admin >
Add	

Select the correct ONVIF protocol authentication and RTSP authentication (both are disabled by default for ZowiePTZ cameras) and click Add to complete the addition.